

IQ PANEL 2 & 2 PLUS - 2.6.1 SOFTWARE UPDATE - RELEASE NOTES AND INSTRUCTIONS

TSB #: 210706

DATE: 07/06/21

RE: IQ PANEL 2 & 2 PLUS - 2.6.1 SOFTWARE UPDATE
RELEASE NOTES & UPDATE INSTRUCTIONS

Release Notes:

New Features:

- Added a new motion detector Sensor Group (45) - Away/Stay Instant Non Follower
- Re-introduced SD Card upgrades with auto-push of "Firmware2" patch from Alarm.com if needed (Wi-Fi connected panels only)
- Now compliant with BS-8243 standards (UK)

Fixes/Improvements:

- Fixed an issue related to SRF sensors identified in TSB 210705
- Stability improvements to dual-path communication connectivity to the Alarm.com backend
- Improved push notification of message center messages while on Photo Frame screensaver
- Improved boot-up after software update
- PowerG activation LED can now be enabled/disabled on previously paired PowerG devices
- Minor improvements to Spanish and Finnish language translations
- Improved Doorbell camera streaming/push notifications from the lock screen
- Alarm.com backend now displays username when arming/disarming from PowerG keypads KP-140, KP-141 & KP-241 with a code
- Fixed an issue with a new improvement in 2.6.0 where silent and audible panics triggered from the Panel are able to report as separate CID codes to the central station
- Fixed an issue introduced in 2.6.0 related to Daily and Weekly Communication Tests signaling to the Central Station

Update Instructions:

Compatibility Note: Your IQ Panel must be on software version 2.0.1 or higher and connected to Wi-Fi to install this update wirelessly. Panels running 2.5.0 & 2.5.1 must be updated to 2.5.3 first, then they can be updated directly to 2.6.1

- 1- Swipe down from the top of the screen and touch "Settings"
- 2- Touch "Advanced Settings"
- 3- Enter a valid installer code (default is 1111)
- 4- Touch "Upgrade Software"
- 5 -Touch "Patch Tag" and enter the patch *iqpanel2.6.1* then touch OK
- 6- Touch "Upgrade Using Network" (panel must be connected to Wi-Fi). Update will download and install
- 7- Once complete touch "OK" to reboot the panel. **DO NOT TOUCH THE SCREEN.** The update process will take approximately 5 minutes. After the panel reboots the home screen will appear and the LED will turn green.